# **Suction System**



### **Features**

#### All in One, saving 50% space

Lafil 400 suction system integrates vacuum source, waste bottle and suction kit into one single system. Saving 50% bench space.

#### Safety features

Multiple safety featured designs protect both the operator and the machine. (1) Tripping-proof and spill-proof fence-like bottle platform.

(2) Overflow protection prevents liquid from entering the pump.

#### Oil-free & care-free

Lafil systems are built-in with oil-free pumps that need no lubricant, making it maintenance-free and oil-mist-free.

#### Autoclavable

The waste bottle and all fittings are made of autoclavable materials such as PES or POM.

- International certification CE certification
- Two-Year Warranty (Lafil 400)

## **Applications**

- Cell culture aspiration
- Laboratory waste suction

# **Ordering Information**

197405-11(22) Lafil 400 - Plus, Suction System

AC110V, 60Hz (AC220V, 50Hz) 197403-11(22)

Lafil 400 - BioDolphin, Suction System AC110V, 60Hz (AC220V, 50Hz)

197400-11(22) Lafil 400, Vacuum Pump AC110V, 60Hz (AC220V, 50Hz)





#### Specification

Model	Lafil 400 - Plus		Lafil 400 - BioDolphin	
PERFORMANCE DATA				
Max. vacuum	25 mbar abs.			
Max. flow rate	23 L/min @60Hz	20 L/min @50Hz	23 L/min @60Hz	20 L/min @50Hz
Aspiration rate	19 mL/sec			
Waste bottle	PES vacuum bottle, 1200 mL			
Noise level	50 dB			
Net weight	7.0 Kg			
Dimension (LxWxH)	34 x 25 x 30 cm			
ELECTRICAL DATA				
Voltage	110V	220V	110V	220V
Frequency	50 / 60Hz		50 / 60Hz	
Max. power	100W	80W	100W	80W
Max. current	1.0A	0.4A	1.0A	0.4A
Safety	Overheat Protection			
OTHER DATA	Plus		BioDolphin	
Suction Kit	<ul> <li>Handle</li> <li>1-channel tip adaptor (150 mm)</li> <li>1-channel tip adaptor with ejector</li> <li>8-channel tip adaptor with ejector</li> </ul>		<ul> <li>Handle</li> <li>1-channel tip adaptor (50 mm)</li> <li>1-channel tip adaptor (150 mm)</li> <li>1-channel SS adaptor (40 mm)</li> <li>1-channel SS adaptor (80 mm)</li> <li>8-channel SS adaptor (40 mm)</li> <li>1-channel tip adaptor with ejector</li> </ul>	

- 8-channel tip adaptor with ejector

• Rack

